

Stability Analysis of Discrete-time Lur'e Systems with Slope-restricted Odd Monotonic Nonlinearities

Kwang Ki Kevin Kim and Richard D. Braatz

Abstract—Many nonlinear dynamical systems can be written as Lur'e systems, which are described by a linear time-invariant system interconnected with a diagonal static sector-bounded nonlinearity. Sufficient conditions are derived for the global asymptotic stability analysis of discrete-time Lur'e systems in which the nonlinearities have restricted slope and/or are odd, which is the usual case in real applications. A Lur'e-Postnikov-type Lyapunov function is proposed that is used to derive sufficient analysis conditions in terms of linear matrix inequalities (LMIs). The derived stability criteria are provably less conservative than criteria published in the literature, with numerical examples indicating that conservatism can be reduced by orders of magnitude.

I. INTRODUCTION

Absolute stability theory considers the stability of a nominal linear time-invariant system interconnected with a static nonlinearity, that is, a real function of real variables with no internal states. The literature on absolute stability theory can be categorized in terms of the properties of the static nonlinearities that are considered. This paper derives new sufficient conditions for the stability analysis of discrete-time systems with the advance being LMI conditions that exploit the static, sector-bounded, and slope-restricted nature of the componentwise nonlinear operators.

Lyapunov methods provide a simple but powerful way to analyze nonlinear dynamical systems and design stabilizing controllers [1], [3], [14], [16], [35]. Many well-known results on absolute stability were developed for a benchmark problem known as the *Lur'e problem* [20], [23], [25], [28]. The Popov and Circle criteria are sufficient frequency-domain conditions for absolute stability for the feedback interconnection of a continuous linear time-invariant system with a sector-bounded nonlinearity [6], [8], [15], [18], [27], [36]. Its discrete-time counterparts are known as the Tsytkin criterion [17], [24] and the Jury-Lee criterion [11]. Consider the nonlinear discrete-time dynamical system:

$$\begin{aligned} x(k+1) &= Ax(k) + Bp(k), \\ q(k) &= Cx(k) + Dp(k), \quad p(k) = -\phi(q(k)), \end{aligned} \quad (1)$$

where $A \in \mathbb{R}^{n \times n}$, $B \in \mathbb{R}^{n \times n_p}$, $C \in \mathbb{R}^{n_q \times n}$, $D \in \mathbb{R}^{n_q \times n_p}$, and the nonlinear operator $\phi \in \Phi$, where Φ is a set of static functions that satisfy $\phi(0) \equiv 0$ and have some specified input-output characteristics. This paper considers several

classes of diagonal nonlinear operators Φ that are defined in Appendix I, in which the individual nonlinearities are sector-bounded, slope-restricted, and/or odd.

Suppose that the state-space system representation (A, B, C, D) is a minimal realization of the transfer function $G(z) = C(zI - A)^{-1}B + D$ such that the triplet (A, B, C) is controllable and observable.¹ It is well known that the frequency-domain sufficient stability conditions—the Circle, Popov and Tsytkin criteria—for the absolute stability of the system (1) can be simply represented by linear matrix inequalities (LMIs) written in terms of the matrices $\{A, B, C, D\}$ via the Positive Real Lemma and the KYP lemma [1], [24], [35]. In this paper the S-procedure converts the constraints on the nonlinearities into LMI conditions, in the same way as in the direct derivation of LMI-based tests for absolute stability [1], [22], [25], [34].² A modified Lur'e-Postnikov function is proposed that produces less conservative conditions for global asymptotic stability. The resulting LMI problems are solved for several numerical examples using off-the-shelf software [7], [29], [19].

II. SUFFICIENT CONDITIONS FOR ASYMPTOTIC STABILITY

A. Modified Lur'e-Postnikov Stability of a Discrete-time Lur'e System

Due to the conservativeness inherent to quadratic Lyapunov functions when applied to nonlinear systems, this section considers the use of a modified Lur'e-Postnikov function that includes integral terms whose sign definiteness are implied by the sector-bounded property of the nonlinear operators ($\phi \in \Phi_{sb}^{[0, \xi]}$). To derive sufficient conditions for the origin of (1) to be globally asymptotically stable, consider the Lyapunov function:

$$\begin{aligned} V(x_k) &= \bar{x}_k^T P \bar{x}_k + 2 \sum_{i=1}^{n_q} Q_{ii} \int_0^{q_{k,i}} \phi_i(\sigma) d\sigma \\ &\quad + 2 \sum_{i=1}^{n_q} \tilde{Q}_{ii} \int_0^{q_{k,i}} [\xi_i \sigma - \phi_i(\sigma)] d\sigma, \end{aligned} \quad (2)$$

This work was supported by the National Science Foundation under Grant #0426328

K. Kim is with the Department of Aerospace Engineering, University of Illinois at Urbana-Champaign, Urbana, IL, 61801, USA kkim78@illinois.edu

R. Braatz is with the University of Illinois at Urbana-Champaign, Urbana, IL, 61801, USA braatz@illinois.edu.

¹Alternatively, the controllability and observability conditions can be removed because strict inequalities will be used in the stability criteria (see Section 2 in [26]). Instead, the condition $\text{Ker} A \cap \text{Ker} B = \{0\}$, which implies that the origin is the one equilibria, is assumed to hold.

²Related results have been derived based on integral quadratic constraints (IQCs) [4], [12], [13], [21], [22], [26] for systems with repeated monotonic or slope-restricted nonlinearities in continuous-time cases.

where

$$\bar{x}_k \triangleq \begin{bmatrix} x_k \\ p_k \\ q_k \end{bmatrix}, \quad P^T = P \triangleq \begin{bmatrix} P_{11} & P_{12} & P_{13} \\ P_{12}^T & P_{22} & P_{23} \\ P_{13}^T & P_{23}^T & P_{33} \end{bmatrix} \geq 0, \quad P_{11} > 0,$$

$$Q_{ii} \geq 0, \quad \tilde{Q}_{ii} \geq 0, \quad \forall i = 1, \dots, n_q,$$

and the subscript k indicates a sampling instance. Both p_k and q_k are functions of the state variable vector x_k , and the above Lyapunov function is radially unbounded and positive for all nonzero $x_k \in \mathbb{R}^n$.

For $P_{12} = 0, P_{13} = 0, P_{22} = 0, P_{23} = 0, P_{33} = 0, \tilde{Q} \triangleq \text{diag}\{\tilde{Q}_{ii}\} = 0$, the Lyapunov function (2) reduces to the Lur'e-Postnikov function used in the derivation of the Popov criterion. All other Lyapunov functions considered in the Lur'e problem literature are subsets of (2). Some papers in the Lur'e stability literature that appear to have additional terms actually just introduce the S-procedure in a different way. The dependence of the Lyapunov function (2) on the nonlinearities and the states provide additional degrees of freedom for reducing conservatism during stability analysis. The application of the S-procedure provides a standard way to consider more restrictive classes of nonlinearities without having modify the Lyapunov function. The degree of conservatism will be compared for sub-problems with different subsets of the Lyapunov function (2), to assess the reduction in conservatism posed by each term.

B. Lagrange Relaxations

Yakubovich showed that the positiveness of a quadratic function $f_0(x)$ in a constraint set expressed in terms of quadratic functions, say $f_i(x)$, $i = 1, \dots, m$, can be implied by the relaxed form with (Lagrange) multipliers. The S-procedure is a special case of Lagrange relaxation in which the constraints are represented in terms of quadratic functions, so that the multipliers can be combined into an LMI inequality. The application of the S-procedure appears not only in control theory but also in the more generic optimization literature. For convenience, below is the form of the S-procedure used in the proofs of this paper.

Lemma 1: (S-procedure for Quadratic Inequalities) For the Hermitian matrices Θ_i , $i = 0, \dots, m$, consider the two sets:

$$(S1) \quad \zeta^* \Theta_0 \zeta < 0, \quad \forall \zeta \in \Phi \triangleq \{\zeta \in \mathbb{F}^n | \zeta^* \Theta_i \zeta \leq 0, \quad \forall i = 1, \dots, m\};$$

$$(S2) \quad \exists \tau_i \geq 0, \quad i = 1, \dots, m \text{ such that } \Theta_0 - \sum_{i=1}^m \tau_i \Theta_i < 0.$$

The feasibility of (S2) implies (S1).

C. Discrete-time Lur'e Systems with Slope-restricted Nonlinearities

While conic-sector bounded nonlinearities, which bound the global slope of the nonlinear functions $\phi(\cdot)$, have been heavily studied in the literature, such a description allows the local slope of the nonlinear functions $\phi(\cdot)$ to vary arbitrarily from one time instance to another. That is, such nonlinearities do not impose any *local* slope restriction. Most nonlinearities in practice have a local slope restriction, in which case a less conservative analysis condition may

be achieved if these constraints on the nonlinearities are included in the analysis via the S-procedure. A local slope restriction also provides an upper bound on the change of the integral term in the Lyapunov function, provided that $\phi(\cdot)$ is continuous almost everywhere (a.e.).

Theorem 1: Consider a system of the form (1) with the memoryless nonlinearity $\phi \in \Phi_{sb}^{[0,\xi]} \cap \Phi_{sr}^{[0,\mu]}$ that is continuous almost everywhere. A sufficient condition for global asymptotic stability is the existence of a positive semidefinite matrix $P = P^T$ with a positive definite submatrix $P_{11} = P_{11}^T$ and diagonal positive semidefinite matrices $Q, \tilde{Q}, T, \tilde{T}, N \in \mathbb{R}^{n_q \times n_q}$ such that

$$G = \begin{bmatrix} G_{11} & G_{12} & G_{13} \\ G_{12}^T & G_{22} & G_{23} \\ G_{13}^T & G_{23}^T & G_{33} \end{bmatrix} < 0 \quad (3)$$

where

$$\begin{aligned} G_{11} = & A^T(P_{11} + P_{13}C + C^T P_{13}^T + C^T P_{33}C)A - P_{11} \\ & - P_{13}C - C^T P_{13}^T - C^T P_{33}C + A^T C^T \tilde{Q} \xi C A \\ & - C^T \tilde{Q} \xi C, \end{aligned}$$

$$\begin{aligned} G_{12} = & A^T(P_{11} + P_{13}C + C^T P_{13}^T + C^T P_{33}C)B - P_{12} \\ & - P_{13}D - C^T P_{23}^T - C^T P_{33}D - C^T T \\ & + (CA - C)^T Q + A^T C^T \tilde{Q} \xi C B + (CA - C)^T \tilde{Q} \\ & - C^T \tilde{Q} \xi D + (CA - C)^T \mu N \end{aligned}$$

$$\begin{aligned} G_{13} = & A^T P_{12} + A^T P_{13}D + A^T C^T P_{23}^T + A^T C^T P_{33}D \\ & - A^T C^T \tilde{T} - (CA - C)^T Q + A^T C^T \tilde{Q} \xi D \\ & - (CA - C)^T \mu N \end{aligned}$$

$$\begin{aligned} G_{22} = & B^T(P_{11} + P_{13}C + C^T P_{13}^T + C^T P_{33}C)B - P_{22} \\ & - P_{23}D - D^T P_{23}^T - D^T P_{33}D - 2\xi^{-1}T - TD \\ & - D^T T + Q(CB - D) + (CB - D)^T Q - \mu^{-1}Q \\ & + B^T C^T \tilde{Q} \xi C B - D^T \tilde{Q} \xi D \\ & + (CB - D)^T \tilde{Q} + \tilde{Q}(CB - D) - \mu^{-1}\tilde{Q} - 2N \\ & + N\mu(CB - D) + (CB - D)^T \mu N \end{aligned}$$

$$\begin{aligned} G_{23} = & B^T P_{12} + B^T P_{13}D + B^T C^T P_{23}^T + B^T C^T P_{33}D \\ & - B^T C^T \tilde{T} + QD + Q\mu^{-1} + \mu^{-1}\tilde{Q} \\ & + \tilde{Q}D + B^T C^T \tilde{Q} \xi D + 2N \\ & - (CB - D)^T \mu N + N\mu D \end{aligned}$$

$$\begin{aligned} G_{33} = & P_{22} + P_{23}D + D^T P_{23}^T + D^T P_{33}D - 2\xi^{-1}\tilde{T} - \tilde{T}D \\ & - D^T \tilde{T} - QD - D^T Q - Q\mu^{-1} - \mu^{-1}\tilde{Q} + D^T \tilde{Q} \xi D \\ & - 2N - N\mu D - D^T \mu N \end{aligned}$$

Proof: The difference in the Lyapunov function (2) between the $k+1$ and k sampling instances is

$$\begin{aligned} \Delta V(x_k) = & \zeta_k^T (A_a^T P A_a - E_a^T P E_a) \zeta_k \\ & + 2 \sum_{i=1}^{n_q} Q_{ii} \int_{q_{k,i}}^{q_{k+1,i}} \phi_i(\sigma) d\sigma \\ & + 2 \sum_{i=1}^{n_q} \tilde{Q}_{ii} \int_{q_{k,i}}^{q_{k+1,i}} [\xi_i \sigma - \phi_i(\sigma)] d\sigma, \end{aligned} \quad (4)$$

where

$$\zeta_k \triangleq \begin{bmatrix} x_k \\ p_k \\ p_{k+1} \end{bmatrix}, A_a \triangleq \begin{bmatrix} A & B & 0 \\ 0 & 0 & I \\ CA & CB & D \end{bmatrix}, E_a \triangleq \begin{bmatrix} I & 0 & 0 \\ 0 & I & 0 \\ C & D & 0 \end{bmatrix}$$

Slope restrictions on the nonlinearities place an upper bound on the first integral:

$$\begin{aligned} & 2 \sum_{i=1}^{n_q} Q_{ii} \int_{q_{k,i}}^{q_{k+1,i}} \phi(\sigma) d\sigma \\ & \leq 2 \sum_{i=1}^{n_q} Q_{ii} \left\{ (\phi_{k+1,i} - \phi_{k,i})(q_{k+1,i} - q_{k,i}) \right. \\ & \quad \left. - \frac{1}{2\mu_i} (\phi_{k+1,i} - \phi_{k,i})^2 \right\} \\ & = \zeta_k^T U_1 \zeta_k, \end{aligned}$$

where U_1 is given in Appendix II. Similarly, an upper bound can be derived on the second integral:

$$\begin{aligned} & 2 \sum_{i=1}^{n_q} \tilde{Q}_{ii} \int_{q_{k,i}}^{q_{k+1,i}} [\xi_i \sigma - \phi(\sigma)] d\sigma \\ & = -2 \sum_{i=1}^{n_q} \tilde{Q}_{ii} \int_{q_{k,i}}^{q_{k+1,i}} \phi(\sigma) d\sigma + 2 \sum_{i=1}^{n_q} \tilde{Q}_{ii} \int_{q_{k,i}}^{q_{k+1,i}} \xi_i \sigma d\sigma \\ & \leq -2 \sum_{i=1}^{n_q} \tilde{Q}_{ii} \left\{ \frac{1}{2\mu_i} (\phi_{k+1,i} - \phi_{k,i})^2 + \phi_{k,i} (q_{k+1,i} - q_{k,i}) \right\} \\ & + \sum_{i=1}^{n_q} \tilde{Q}_{ii} \xi_i [q_{k+1,i}^2 - q_{k,i}^2] \\ & = \zeta_k^T U_2 \zeta_k, \end{aligned}$$

where U_2 is given in Appendix II.

Since the (negative) feedback-connected nonlinearity is monotonic with slope restriction in addition to being $[0, \xi]$ sector-bounded, i.e., $\phi \in \Phi_{sb}^{[0, \xi]} \cap \Phi_{sr}^{[0, \mu]}$, it can be shown that the following inequalities are satisfied at each sampling instance k and all indices $i = 1, \dots, n_q$:

$$\phi_{k,i} [\xi_i^{-1} \phi_{k,i} - q_{k,i}] \leq 0, \quad (5)$$

$$(\phi_{k+1,i} - \phi_{k,i}) [\mu_i^{-1} (\phi_{k+1,i} - \phi_{k,i}) - (q_{k+1,i} - q_{k,i})] \leq 0. \quad (6)$$

The following notations based on (5) are useful when applying the S-procedure:

$$\sum_{i=1}^{n_q} 2\tau_i \phi_{k,i} [\xi_i^{-1} \phi_{k,i} - q_{k,i}] = \zeta_k^T S_1 \zeta_k, \quad (7)$$

$$\sum_{i=1}^{n_q} 2\tilde{\tau}_i \phi_{k+1,i} [\xi_i^{-1} \phi_{k+1,i} - q_{k+1,i}] = \zeta_k^T S_2 \zeta_k, \quad (8)$$

where S_1 and S_2 are given in Appendix II. A similar notation based on the inequality (6) is:

$$\begin{aligned} & \sum_{i=1}^{n_q} 2N_{ii} (\phi_{k+1,i} - \phi_{k,i}) [\mu_i^{-1} (\phi_{k+1,i} - \phi_{k,i}) - (q_{k+1,i} - q_{k,i})] \\ & = \zeta_k^T S_3 \zeta_k, \end{aligned} \quad (9)$$

where S_3 is given in Appendix II.

Applying the S-procedure, if the LMI $G \triangleq A_a^T P A_a - E_a^T P E_a + U_1 + U_2 - S_1 - S_2 - S_3 < 0$ is feasible then $\Delta V(x_k) < 0$ is satisfied for the specific class of feedback-connected nonlinearities $\phi \in \Phi_{sb}^{[0, \xi]} \cap \Phi_{sr}^{[0, \mu]}$. All of introduced matrix (decision) variables are of compatible dimensions. $\square$

Remark 1: The upper bounds on the integral terms in (4) are derived by considering the a.e. continuity of the nonlinearity $\phi(\cdot)$. In those upper bounds the slope-restricted properties of the nonlinear feedback are exploited, which gives sharper bounds than the upper bounds in [9], [10], [14].

D. Discrete-time Lur'e Systems with Slope-restricted and Odd Monotonic Nonlinearities

Theorem 1 exploits more information on the nonlinear operator than the original Lur'e problem. This section derives a less conservative sufficient stability condition for the more restrictive class of nonlinearities that are odd monotonic, by the introduction of additional quadratic constraints.

Theorem 2: Consider a system of the form (1) with the memoryless nonlinearity $\phi \in \Phi_{sb}^{[0, \xi]} \cap \Phi_{sr}^{[0, \mu]} \cap \Phi_{odd}$, which is continuous almost everywhere. A sufficient condition for global asymptotic stability is the existence of a positive semidefinite matrix $P = P^T$ with a positive definite submatrix $P_{11} = P_{11}^T$ and diagonal positive semidefinite matrices $Q, \tilde{Q}, T, \tilde{T}, N, L$, and $\tilde{L} \in \mathbb{R}^{n_q \times n_q}$ such that

$$\bar{G} = \begin{bmatrix} \bar{G}_{11} & \bar{G}_{12} & \bar{G}_{13} \\ \bar{G}_{12}^T & \bar{G}_{22} & \bar{G}_{23} \\ \bar{G}_{13}^T & \bar{G}_{23}^T & \bar{G}_{33} \end{bmatrix} < 0 \quad (10)$$

where

$$\begin{aligned} \bar{G}_{11} &= G_{11} \\ \bar{G}_{12} &= G_{12} - (CA - C)^T L - (CA + C)^T \tilde{L} \\ \bar{G}_{13} &= G_{13} - (CA - C)^T L - (CA - C)^T \tilde{L} \\ \bar{G}_{22} &= G_{22} - (CB - D)^T L - L(CB - D) \\ &\quad - (CB + D)^T \tilde{L} - \tilde{L}(CB + D) \\ \bar{G}_{23} &= G_{23} - (CB - D)^T L - LD - \xi^{-1} L \\ &\quad - (CB - D)^T \tilde{L} - \tilde{L}D + \xi^{-1} \tilde{L} \\ \bar{G}_{33} &= G_{33} - D^T L - LD - \tilde{L}D - D^T \tilde{L} \end{aligned}$$

Proof: The difference in the Lyapunov function (2) between the $k+1$ and k sampling instances is the same as $\Delta V(x_k)$ in (4) with the same definitions of ζ_k, A_a , and E_a . Sector-bounded, slope-restricted, odd-monotonic feedback-connected nonlinearities satisfy (5) and (6) at each sampling time k and all indices $i = 1, \dots, n_q$ for $\phi \in \Phi_{sb}^{[0, \xi]} \cap \Phi_{sr}^{[0, \mu]} \cap \Phi_{odd}$ and satisfy

$$(q_{k+1,i} - q_{k,i}) [\phi_{k+1,i} + \phi_{k,i}] - \phi_{k,i} \frac{1}{\xi_i} \phi_{k+1,i} \geq 0, \quad (11)$$

$$\begin{aligned} & (q_{k+1,i} - q_{k,i}) [\phi_{k+1,i} + \phi_{k,i}] - \phi_{k,i} \frac{1}{\xi_i} \phi_{k+1,i} \\ & \leq 2q_{k+1,i} \phi_{k+1,i}. \end{aligned} \quad (12)$$

The following notations are motivated by (11) and (12):

$$\sum_{i=1}^{n_q} 2L_{ii} \left\{ \phi_{k,i} \xi_i^{-1} \phi_{k+1,i} - (q_{k+1,i} - q_{k,i})(\phi_{k+1,i} + \phi_{k,i}) \right\} = \zeta_k^T S_4 \zeta_k, \quad (13)$$

and

$$\sum_{i=1}^{n_q} 2\tilde{L}_{ii} \left\{ \begin{array}{c} q_{k,i}(\phi_{k+1,i} - \phi_{k,i}) - q_{k+1,i}(\phi_{k+1,i} + \phi_{k,i}) \\ -\phi_{k,i} \frac{1}{\xi_i} \phi_{k+1,i} \end{array} \right\} = \zeta_k^T S_5 \zeta_k, \quad (14)$$

where S_4 and S_5 are given in Appendix II.

If the LMI $G = A_a^T P A_a - E_a^T P E_a + U_1 + U_2 - S_1 - S_2 - S_3 - S_4 - S_5 < 0$ is feasible then $\Delta V(x_k) < 0$ is satisfied for the class of feedback-connected nonlinearities $\phi \in \Phi_{sb}^{[0,\xi]} \cap \Phi_{sr}^{[0,\mu]} \cap \Phi_{odd}$. All of matrix (decision) variables introduced are of compatible dimensions. $\square$

Remark 2: The inequality constraints over the odd monotonic nonlinearities (11) and (12) can be found in [23], [31], [32]. The inequalities (11) and (12) are written in terms of quadratic functions of ζ_k , so that the S-procedure is applied to combine the constraints with the negative definite condition over $\Delta V(x_k)$.

Remark 3: (Frequency-domain inequalities) The well-known KYP lemma replaces an LMI with an equivalent frequency-domain inequality (FDI) in terms of the system transfer function [33]. The FDI provides a graphical tool to determine feasibility of the LMI for systems with one nonlinearity, i.e., $n_p = n_q = 1$, such as used in the graphical implementation of the Popov stability criterion. It is straightforward to apply the KYP lemma to transform each LMI (3) and (10) into an FDI (not shown for space considerations).

Theorem 1 and 2 described LMI feasibility problems. That is, each criterion considers whether the set $\{X \in \mathbb{S}^n | \Psi(X) < 0, X \geq 0\}$ is empty or non-empty. The following lemma shows the equivalence between two sets of matrix decision variables.

Lemma 2: (Feasibility considerations) The set of symmetric matrices affine in X , $\{X \in \mathbb{S}^n | \Psi(X) < 0, X \geq 0\}$, is nonempty if and only if the set of symmetric matrices, $\{X \in \mathbb{S}^n | \Psi(X) < 0, X > 0\}$ is nonempty.

Proof: The (only if) part is obvious. To prove the (if) part, the LMIs in the set can be rewritten as:

$$\Psi(X) = F_0 + \sum_{i=1}^N x_i F_i, \quad (15)$$

where $X = X^T \in \mathbb{R}^{n \times n}$, $N = n(n+1)/2$, and the F_i are of compatible dimension. Suppose that $X^0 \in \{X \in \mathbb{S}^n | \Psi(X) < 0, X \geq 0\}$. With the definition $X^\delta \triangleq X^0 + \delta I$, $X^\delta > 0$ for any value of positive scalar $\delta > 0$. Now show that there exists a scalar $\delta > 0$ such that X^δ is in the set $\{X \in \mathbb{S}^n | \Psi(X) < 0, X > 0\}$. Consider

$$\Psi(X^\delta) = F_0 + \sum_{i=1}^N (x_i + \delta_i) F_i, \quad (16)$$

where $\delta_i \in \{0, \delta\}$ for each $i = 1, \dots, N$ and the number of nonzero δ_i is n . Since the eigenvalues of $\Psi(X^\delta)$ are continuous for $\delta \rightarrow 0$, these eigenvalues approach the eigenvalues of $\Psi(X^0)$ as $\delta \rightarrow 0$. In particular, for sufficiently small δ the eigenvalues of $\Psi(X^\delta)$ have negative real part so that $\Psi(X^\delta) < 0$. $\square$

Remark 4: (Computation for strict and non-strict LMIs) From the results of Lemma 2, any LMI solver that is guaranteed to converge for an LMI feasibility problem with strict inequalities will converge for the above LMI feasibility problems.

III. NUMERICAL EXAMPLES FOR STABILITY ANALYSIS

Numerical examples are provided to illustrate the analysis results in Section II. All LMI computations were performed with *MATLAB's LMI Control Toolbox*. The sector bounds ξ_i and slope restrictions μ_i in each element ϕ_i of the nonlinearities were taken to be the same. The maximum upper bound on the ξ was computed, where μ was taken to be linear in ξ , as shown in each example. A large enough value for ξ makes the LMI in Theorem 1 (or 2) infeasible. A small enough value for ξ makes the LMI feasible provided that the system is nominally stable, that is, the system without nonlinearities is stable. These two values provide upper and lower bounds for the value of ξ for which the LMI switches from being feasible to being infeasible. The maximum ξ for which the LMI in each criterion is feasible were computed by the bisection method.

As discussed in Section II, the proposed stability criteria were derived for a Lyapunov function that has more degrees of freedom than past stability criteria and so have the potential for being less conservative. Table 1 shows that the criteria in Theorems 1 and 2 are less conservative for six numerical examples. As expected, the stability margins are larger when more information is provided on the nonlinearities connected with the LTI system, and Theorems 1 and 2 provide more accurate estimates of the upper bound on ξ or μ . Although Theorems 1 and 2 apply to semiproper and strictly proper systems, the numerical examples only include strictly proper systems to allow comparison to the other criteria in the literature, which assume $D \equiv 0$.

Example 1 is from [24] ($\mu = 2\xi$):

$$G(z) = \frac{-0.5z + 0.1}{(z^2 - z + 0.89)(z + 0.1)}$$

TABLE I
THE MAXIMAL UPPER BOUND ON THE SECTOR BOUND

Stability Criterion	Ex 1	Ex 2	Ex 3	Ex 4	Ex 5	Ex 6
Circle ($\phi \in \Phi_{sb}^{[0,\xi]}$)	1.0273	0.18358	0.21792	2.91387	0.03660	0.03716
Tsykin ($\phi \in \Phi_{sb}^{[0,\xi]}$)	1.0273	0.18358	0.21792	2.91387	0.03660	0.03716
Haddad et al. ($\phi \in \Phi_{sb}^{[0,\xi]} \cap \Phi_{sr}^{[0,\mu]}$)	1.0273	0.18358	0.21792	2.91387	0.03660	0.03716
Kapila et al. ($\phi \in \Phi_{sb}^{[0,\xi]} \cap \Phi_{sr}^{[0,\infty]}$)	1.0273	0.18358	0.21792	2.91387	0.03660	0.03716
Park et al. ($\phi \in \Phi_{sb}^{[0,\xi]} \cap \Phi_{sr}^{[0,\infty]}$)	1.7252	0.18358	0.21792	2.91387	0.03660	0.03716
Theorem 1 ($\phi \in \Phi_{sb}^{[0,\xi]} \cap \Phi_{sr}^{[0,\mu]}$)	2.4475	0.73082	0.30203	43.40412	19.18289	0.04613
Theorem 2 ($\phi \in \Phi_{sb}^{[0,\xi]} \cap \Phi_{sr}^{[0,\mu]} \cap \Phi_{odd}$)	2.5576	0.73082	0.83686	43.40412	19.18289	0.18975

Example 2 has 5 states and 2 nonlinearities ($\mu = \xi$):

$$A = \begin{bmatrix} 0.2948 & 0 & 0 & 0 & 0 \\ 0 & 0.4568 & 0 & 0 & 0 \\ 0 & 0 & 0.0226 & 0 & 0 \\ 0 & 0 & 0 & 0.3801 & 0 \\ 0 & 0 & 0 & 0 & -0.3270 \end{bmatrix},$$

$$B = \begin{bmatrix} -1.1878 & 0.2341 \\ -2.2023 & 0.0215 \\ 0.9863 & -1.0039 \\ -0.5186 & -0.9471 \\ 0.3274 & -0.3744 \end{bmatrix},$$

$$C = \begin{bmatrix} -1.1859 & 1.4725 & -1.2173 & -1.1283 & -0.2611 \\ -1.0559 & 0.0557 & -0.0412 & -1.3493 & 0.9535 \end{bmatrix}.$$

Example 3 has a dense A -matrix and 2 nonlinearities ($\mu = \xi$):

$$A = \begin{bmatrix} 0.0469 & -0.3992 & -0.0835 \\ 0.3902 & -0.5363 & -0.2744 \\ 0.4378 & -1.3576 & 0.4651 \end{bmatrix},$$

$$B = \begin{bmatrix} -0.5673 & -0.2785 \\ 0.1155 & -0.0649 \\ -2.1849 & -0.5976 \end{bmatrix},$$

$$C = \begin{bmatrix} 0.3587 & -1.0802 & -0.6802 \\ -1.3833 & -1.0677 & 1.1497 \end{bmatrix}.$$

Example 4 has two poles at the same location ($\mu = 2\xi$):

$$A = \begin{bmatrix} 0.4030 & 0 & 0 \\ 0 & -0.1502 & 0 \\ 0 & 0 & -0.1502 \end{bmatrix}, B = \begin{bmatrix} -0.2494 \\ 0.2542 \\ -0.2036 \end{bmatrix},$$

$$C = [0.9894 \quad 0.6649 \quad 0.4339].$$

Example 5 has three poles at the same location ($\mu = 2\xi$):

$$A = \begin{bmatrix} 0.4783 & 0 & 0 & 0 \\ 0 & 0.7871 & 0 & 0 \\ 0 & 0 & 0.7871 & 1 \\ 0 & 0 & 0 & 0.7871 \end{bmatrix},$$

$$B = \begin{bmatrix} -1.5174 \\ 1.2181 \\ 0.2496 \\ -0.5181 \end{bmatrix},$$

$$C = [0.8457 \quad -2.0885 \quad 1.2190 \quad 0.1683].$$

Example 6 has a wide range of pole locations including two poles near 1 ($\mu = \xi$):

$$A = \text{diag}\{0.5359, 0.9417, 0.9802, 0.5777, -0.1227, -0.0034, -0.5721, 0.2870, -0.3599\},$$

$$B = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & 0 & 0 \end{bmatrix},$$

$$C = \begin{bmatrix} 1 & 1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 1 & 1 & 1 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 & 1 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 & 1 \end{bmatrix}.$$

The stability margins for Example 5 indicate that Theorem 1 can reduce the conservatism compared to literature results by more than 53,200%. The stability margins for Example 6 indicate that, for odd nonlinearities, Theorem 2 can reduce the conservatism by more than 400% compared to Theorem 1 and even more when compared to literature results.

IV. CONCLUSIONS

This paper considers the analysis of global asymptotic stability for discrete-time Lur'e systems with nonlinearities of various types. The proposed Lyapunov function (2) is a superset of all past reported Lyapunov functions, and the new sufficient conditions for globally asymptotic stability are less conservative. Conservatism is further reduced for nonlinear operators that satisfy additional constraints in input and output behavior, such as being odd or having local slope restrictions. Numerical examples indicate that the reduction in conservatism can be many orders of magnitude. The results can be generalized to the analysis of L_2 -gain, root-mean-square gain, and decay rate in the standard way [1].

REFERENCES

- [1] S. Boyd, L. El Ghaoui, E. Feron, and V. Balakrishnan, *Linear Matrix Inequalities in System and Control Theory*, SIAM, Philadelphia, PA, 1994.
- [2] V. Balakrishnan and R. L. Kashyap, Robust stability and performance analysis of uncertain systems using linear matrix inequalities. *J. of Optimization Theory & Applications*, vol. 100, pp. 457–478, 1999.

APPENDIX I
DEFINITIONS FOR SOME CLASSES OF NONLINEAR OPERATORS

$$\begin{aligned}\Phi_{sb}^{[0,\xi]} &\triangleq \{\phi : \mathbb{R}^{n_q} \rightarrow \mathbb{R}^{n_q} \mid \phi_i(\sigma) [\xi_i^{-1} \phi_i(\sigma) - \sigma] \leq 0, \forall \sigma \in \mathbb{R} \text{ and for } i = 1, \dots, n_q\}; \\ \Phi_{sr}^{[0,\mu]} &\triangleq \{\phi : \mathbb{R}^{n_q} \rightarrow \mathbb{R}^{n_q} \mid 0 \leq \frac{\phi_i(\sigma) - \phi_i(\hat{\sigma})}{\sigma - \hat{\sigma}} \leq \mu_i, \forall \sigma \neq \hat{\sigma} \in \mathbb{R} \text{ and for } i = 1, \dots, n_q\}; \\ \Phi_{odd} &\triangleq \{\phi : \mathbb{R}^{n_q} \rightarrow \mathbb{R}^{n_p} \mid \phi_i(\sigma) = -\phi_i(-\sigma), \forall \sigma \in \mathbb{R} \text{ and for } i = 1, \dots, n_q\}.\end{aligned}$$

APPENDIX II
MATRICES FOR THE APPLICATION OF THE S-PROCEDURE IN THEOREMS 1 AND 2

$$\begin{aligned}U_1 &\triangleq \begin{bmatrix} 0 & (CA - C)^T Q & -(CA - C)^T Q \\ * & Q(CB - D) + (CB - D)^T Q - Q\mu^{-1} & QD + Q\mu^{-1} \\ * & * & -QD - D^T Q - Q\mu^{-1} \end{bmatrix} \\ U_2 &\triangleq \begin{bmatrix} A^T C^T \tilde{Q} \xi C A - C^T \tilde{Q} \xi C & A^T C^T \tilde{Q} \xi C B + (CA - C)^T \tilde{Q} - C^T \tilde{Q} \xi D & A^T C^T \tilde{Q} \xi D \\ * & \begin{pmatrix} B^T C^T \tilde{Q} \xi C B - D^T \tilde{Q} \xi D \\ +(CB - D)^T \tilde{Q} + \tilde{Q}(CB - D) - \mu^{-1} \tilde{Q} \end{pmatrix} & \mu^{-1} \tilde{Q} + \tilde{Q}D + B^T C^T \tilde{Q} \xi D \\ * & * & -\mu^{-1} \tilde{Q} + D^T \tilde{Q} \xi D \end{bmatrix} \\ S_1 &\triangleq \begin{bmatrix} 0 & C^T T & 0 \\ * & 2\xi^{-1}T + TD + D^T T & 0 \\ * & * & 0 \end{bmatrix}, \quad S_2 \triangleq \begin{bmatrix} 0 & 0 & A^T C^T \tilde{T} \\ * & 0 & B^T C^T \tilde{T} \\ * & * & 2\xi^{-1}\tilde{T} + \tilde{T}D + D^T \tilde{T} \end{bmatrix} \\ S_3 &\triangleq \begin{bmatrix} 0 & -(CA - C)^T N & (CA - C)^T N \\ * & 2N\mu^{-1} - (CB - D)^T N - N(CB - D) & -2N\mu^{-1} + (CB - D)^T N - ND \\ * & * & 2N\mu^{-1} + D^T N + ND \end{bmatrix} \\ S_4 &\triangleq \begin{bmatrix} 0 & (CA - C)^T L & (CA - C)^T L \\ * & (CB - D)^T L + L(CB - D) & (CB - D)^T L + LD + \xi^{-1}L \\ * & * & D^T L + LD \end{bmatrix} \\ S_5 &\triangleq \begin{bmatrix} 0 & (CA + C)^T \tilde{L} & (CA - C)^T \tilde{L} \\ * & (CB + D)^T \tilde{L} + \tilde{L}(CB + D) & (CB - D)^T \tilde{L} + \tilde{L}D - \xi^{-1}\tilde{L} \\ * & * & D^T \tilde{L} + \tilde{L}D \end{bmatrix}.\end{aligned}$$

-
- [3] X. Chen and J. T. Wen, "Robustness analysis of LTI systems with structured incrementally sector bounded nonlinearities," in *Proc. of the American Control Conference*, pp. 3883–3887, Piscataway, NJ, 1995.
- [4] F. J. D'Amato, M. A. Rotea, A. V. Megretski, and U. Jönsson, New results for analysis of systems with repeated nonlinearities, *Automatica*, vol. 37, pp. 739–747, 2001.
- [5] C. A. Desoer and M. Vidyasagar, *Feedback Systems: Input-Output Properties*, Academic Press, New York, NY, 1975.
- [6] S. Gupta and S. M. Joshi, "Some properties and stability results for sector-bounded LTI systems," *Proc. of the 33rd Conference on Decision and Control*, Lake Buena Vista, FL, 1994.
- [7] P. Gahinet, A. Nemirovski, A. J. Laub, and M. Chilali, *LMI Control Toolbox User's Guide*, The MathWorks, Inc., Natick, MA, 1995.
- [8] W. M. Haddad and D. S. Bernstein, Explicit construction of quadratic Lyapunov functions for the small gain, positivity, circle, and Popov theorems and their application to robust stability, Part II: discrete-time theory, *Int. J. of Robust & Nonlinear Control*, vol. 4, pp. 249–265, 1994.
- [9] W. M. Haddad and D. S. Bernstein, Parameter-dependent Lyapunov functions and the discrete-time Popov criterion for robust analysis, *Automatica*, vol. 30, pp. 1015–1021, 1994.
- [10] W. M. Haddad and V. Kapila, Absolute stability criteria for multiple slope-restricted monotonic nonlinearities, *IEEE Trans. on Automatic Control*, vol. 40, pp. 361–365, 1995.
- [11] E. I. Jury and B. W. Lee, On the stability of a class of nonlinear sampled-data systems, *IEEE Trans. on Automatic Control*, vol. 9, pp. 51–61, 1964.
- [12] U. Jönsson and A. Megretski, "The Zames-Falb IQC for critically stable systems," in *Proc. of the American Control Conference*, Philadelphia, PA, 1998.
- [13] U. Jönsson, Stability analysis with Popov multipliers and integral quadratic constraints, *Systems & Control Letters*, vol. 31, pp. 85–92, 1997.
- [14] V. Kapila and W. M. Haddad, A multivariable extension of the Tsyppkin criterion using a Lyapunov-function approach, *IEEE Trans. on Automatic Control*, vol. 41, pp. 149–152, 1996.
- [15] H. K. Khalil, *Nonlinear Systems*, third edition, Prentice-Hall, Englewood Cliffs, NJ, 2002.
- [16] K. Konishi and H. Kokame, Robust stability of Lur'e systems with time-varying uncertainties: A linear matrix inequality approach, *Int. J. of Systems Science*, vol. 30, pp. 3–9, 1999.
- [17] M. Larsen and P. V. Kokotovic, A brief look at the Tsyppkin criterion: From analysis to design, *Int. J. of Adaptive Control & Signal Processing*, vol. 15, pp. 121–128, 2001.
- [18] S. M. Lee and J. H. Park, Robust stabilization of discrete-time nonlinear Lur'e systems with sector and slope restricted nonlinearities, *Applied Mathematics & Computation*, vol. 200, pp. 429–436, 2008.
- [19] J. Lofberg, "Modeling and solving uncertain optimization problems in YALMIP," in *Proc. of the 17th IFAC World Congress*, South Korea, 2008.
- [20] K. R. Meyer, Lyapunov functions for the problem of Lur'e, *Proc. of the National Academy of Sciences of the United States of America*, vol. 53, pp. 501–503, 1965.
- [21] A. Megretski and A. Rantzer, Systems analysis via integral quadratic constraints, *IEEE Trans. on Automatic Control*, vol. 42, pp. 819–830, 1997.

- [22] A. Megretski and S. Treil, Power distribution inequalities in optimization and robustness of uncertain systems, *J. of Mathematical Systems, Estimation, and Control*, vol. 3, pp. 301–319, 1993.
- [23] K. S. Narendra and J. H. Taylor, *Frequency Domain Criteria for Absolute Stability*, Academic Press, New York and London, 1973.
- [24] P. Park and S. W. Kim, A revisited Tsyppkin criterion for discrete-time nonlinear Lur’e systems with monotonic sector-restrictions, *Automatica*, vol. 34, pp. 1417–1420, 1998.
- [25] P. Park, Stability criteria of sector- and slope-restricted Lur’e systems, *IEEE Trans. on Automatic Control*, vol. 47, pp. 308–313, 2002.
- [26] A. Rantzer, On the Kalman-Yakubovich-Popov lemma, *Systems & Control Letters*, vol. 28, pp. 7–10, 1996.
- [27] V. Singh, A stability inequality for nonlinear feedback systems with slope-restricted nonlinearity, *IEEE Trans. on Automatic Control*, vol. 29, pp. 743–744, August 1984.
- [28] T. N. Sharma and V. Singh, On the absolute stability of multivariable discrete-time nonlinear systems, *IEEE Trans. on Automatic Control*, vol. 26, pp. 585–586, 1981.
- [29] J. F. Sturm, Using SeDuMi 1.02, a MATLAB toolbox for optimization over symmetric cones, *Optimization Methods & Software*, vol. 11–12, pp. 625–653, 1999.
- [30] J. A. K. Suykens, J. Vandewalle, and B. De Moor, An absolute stability criterion for the Lur’e problem with sector and slope restricted nonlinearities, *IEEE Trans. on Circuits & Systems-I: Fundamental Theory & Applications*, vol. 45, pp. 1007–1009, 1998.
- [31] M. A. L. Thathachar and M. D. Srinath, Some aspects of the Lur’e problem, *IEEE Trans. on Automatic Control*, vol. 12, pp. 451–453, 1967.
- [32] M. A. L. Thathachar, M. D. Srinath and H. K. Ramapriyan, On a modified Lur’e problem, *IEEE Trans. on Automatic Control*, vol. 12, pp. 731–740, 1967.
- [33] J. C. Willems, Least squares stationary optimal control and the algebraic Riccati equation, *IEEE Trans. on Automatic Control*, vol. 16, pp. 621–634, 1971.
- [34] V. A. Yakubovich, Nonconvex optimization problem: The infinite-horizon linear-quadratic control problem with quadratic constraints, *Systems & Control Letters*, vol. 19, pp. 13–22, 1992.
- [35] C. Yang, Q. Zhang, and L. Zhou, Lur’e lyapunov functions and absolute stability criteria for Lur’e systems with multiple nonlinearities, *Int. J. of Robust & Nonlinear Control*, vol. 30, pp. 829–841, 2007.
- [36] G. Zames and P. L. Falb, Stability conditions for systems with monotone and slope-restricted nonlinearities, *SIAM J. of Control*, vol. 6, pp. 89–108, 1968.